


SSD04

Sensorless brushless motor drive circuit



For Micro DC brushless motors SBL02-06 and SBL04-08

Description

SSD04 is a 3-phase sensorless drive circuit designed to operate brushless motor SBL02-06 and SBL04-08 exclusively. The operating voltage can be adjusted by VR trimmer and motor shaft direction can be reversed by connecting CW/CCW input to Vcc, if not connected the SBL02-06 runs CW while SBL04-08 CCW. FG (Frequency Generator) output provides a pulse per motor revolution. Internal thermal protection circuit included.

Specifications

	SSD04			
	Min.	Typ.	Max.	
Voltage supply	2.7		6.0	V
Output voltage			4.9	V
Output current			0.8	A
Operating temperature range	-20 ... +75			°C
Weight	1.9			g